

Copper Tube Crimp Terminals



Product Overview

- All copper tube terminals have bell mouth entry for ease of cable insertion.
- All terminals have inspection holes to check cable is properly inserted before crimping.
- Copper tube splices, four hole transformer fixing, long palm, right angle, blank terminals, copper pins, dissimilar copper splices and flag terminals also available on request.
- Sizes above 400mm² available on request.
- Other Stud sizes available on request.

Specification:

Material: High conductivity copper to BS 2871.

Purity: > 99.9%

Coating: Bright electro-tin plating to BS 1872.

Entry: Bell-mouth easy entry.

Barrels: Internal Barrel diameters suit standard cables as defined in BS 6360.

Copper Tube Terminals

Part No.	Conductor Cross-sectional Area (mm ²)	Stud Size (mm) (Please Specify) (Eg. col 10-5)
COL 1.5	1.5	4, 5
COL 2.5	2.5	4, 5, 6
COL 4	4	4, 5, 6
COL 6	6	4, 5, 6, 8, 10
COL 10	10	5, 6, 8, 10, 12
COL 16	16	5, 6, 8, 10, 12
COL 25	25	5, 6, 8, 10, 12
COL 35	35	6, 8, 10, 12
COL 50	50	6, 8, 10, 12, 14, 16
COL 70	70	6, 8, 10, 12, 14, 16
COL 95	95	8, 10, 12, 14, 16
COL 120	120	8, 10, 12, 14, 16
COL 150	150	10, 12, 14, 16, 20
COL 185	185	10, 12, 14, 16, 20
COL 240	240	10, 12, 14, 16, 20
COL 300	300	10, 12, 14, 16, 20
COL 400	400	10, 12, 14, 16, 20